VGA @BIOS SOP

—, @BIOS installation



Step1. Double-click the icon.

🗒 GIGABYTE VGA @BIOS - Ins	tallShield Wizard	
U	Welcome to the InstallShield Wiz GIGABYTE VGA @BIOS	ard for
	The InstallShield(R) Wizard will allow you to remove GIGABYTE VGA @BIOS. To continue	modify, repair, or :, dick Next.
A		
4		
	< Back Next >	Cancel

Step2. Click the **Next** botton.

岗 GIGABYTE VGA @BIOS - InstallShiel	d Wizard		
Ready to Install the Program			
The wizard is ready to begin installation	on.		- Anna
Click Install to begin the installation.			
If you want to review or change any o exit the wizard.	of your installation sett	ings, dick Back. Click Car	ncel to
InstallShield			
	< Back	Install	ancel

Step3. Click the **Install** botton.

👸 GIGABYTE VGA @BIOS - Ins	tallShield Wizard	X
E	InstallShield Wizard Completed	
	The InstallShield Wizard has successfully installed GIGABYTE VGA @BIOS. Click Finish to exit the wizard.	
	< Back Finish Cancel	

Step4.Click the **Finish** botton.

\equiv , @BIOS instructions

After @BIOS installation, click start you will find the icon

GIGABYTE VGA @BIOS

then click it.

You can check the current BIOS version of the card from the BIOS VERSION. Before flashing Bios, you have to save the current Bios first.

CURRENT VGA CAR	
N98XPZL-1GH F2	BACKUP VGA BIOS
64401-4	FLASH
61440 bytes	EXIT
	GIGABYTE
	CURRENT VGA CAR INFORMATION N98XPZL-1GH F2 61440 bytes

Step1. Click BACKUP VGA BIOS button.

Save in:	📗 atBIOS			- *	• 🖻 💣	EE ▼
P z	Name	Date modif	Туре	Size		
ent Places	🎩 skin					
	🗼 tool					
	GBDrvUt	il.dll				
esktop	GPCIDrv.	sys				
1 R	GPCIDrv(b4.sys				
888 888	GVELASE					
		1 J eve manifect				
3		i.exe.mannest				
mputer	MEC71.d	II.				
	M mfc71u.0	10				
etwork	msvcr71.	dll				
	N98XPZL	1GH.F2				
	Cla anna i		20.52		-	Court
	File name:	IN96XPZL-I	an.rz			Jave

Step2. Select the target file to save BIOS.

BIOS CURRENT VGA CAP	•
BIOS VERSION : N98XPZL-1GH F2	BACKUP VGA BIOS
EEPPON SIZE . 61440 hidaa	FLASH
01440 bytes	EXIT
ase wait a moment DO NOT shut down this computer	GIGABYTE
e screen may go *BLANK* during EEPROM fl	ash
ОК	

Step3. Click the **OK** button.

@BIOS CURRENT VGA CARD	000
BIOS VERSION : N98XPZL-1GH F2	BACKUP VGA BIOS
EEPROM SIZE 61440 butes	FLASH
UI440 Dytes	EXIT
lease wait a momentDO NOT shut down this computer	GIGABYTE
ave VGA BIOS complated!!!	
OK	

Step4. Click **OK** button to save VGA BIOS.

@BIOS	CURRENT VGA CARD	000
BIOS VERSION :	N98XPZL-1GH F2	BACKUP VGA BIOS
ERPROM SIZE	CHARLES	FLASH
EEPROM SIZE .	6 1440 bytes	EXIT
eady		GIGABYTE"

Step5. Click FLASH.

Select source f	ile to update l	BIOS				-X-
Look in:	🔒 atBIOS			- + 1	I 💣 💷 🔻	
C.	Name	Date modif	Туре	Size		
Recent Places	J skin J tool ⊗ GBDrvUt	il.dll				
Desktop	GPCIDrv GPCIDrv	.sys 64.sys				
aaa	GVFLASH	H.CFG H				
Computer	GVFLASH	H.exe.manifest				
Network	MFC/1.c	dll				
		L-1GH.F2				
	File name:	1			<u> </u>	Open
	Files of type:					Cancel

Step6. Select source file to update BIOS.

BIOS CURRENT VGA CARD	1
IOS VERSION : N98XPZL-1GH F2	BACKUP VGA BIOS
	FLASH
ET ROM VIZE 61440 bytes	EXIT
Flash BIOS complated!!!	GIGABYTE
	N. S. Statement of State

Step7. Click the **OK** botton to finish flashing BIOS.

!Warning: Because BIOS flashing is potentially risky, if you do not encounter problems using the current version of BIOS, It is recommended that you not flash the BIOS.